

Instruction manual

USER'S MANUAL



Professional wireless walkie-talkie

PROFESSIONAL FM TRANSCEIVER

Q30 disc wireless meal pickup operation instructions

1. Parameter description

Parameter description			
Host		Extension	
Dimensions	200*160*33mm	Dimensions	80*13.5mm
weight	426 Gram	Weight	35 Grams
Shell material	ABS	Shell material	PC
Transmit power	110mW	Receiving frequency	433MHz
Standby power consumption	90mW	Receiving sensitivity	-114dB
Maximum power	27W	Battery capacity	350mAh Lithium battery
Power supply	5V6A	Open distance	200 meters
Number of charges	16 pcs	Prompt method	Vibration, beep, LED flashing

2. Operation instructions

First open the packaging box, plug the power supply 5V6A into the host power supply hole, install the antenna on the corresponding hole, and then put each sub-machine into the host charging slot. The general charging time is 5-10 minutes, and then perform the code operation. The corresponding number has been set by default at the factory.

3. Extension button function

- ① Press and hold the orange button on the front for 3 seconds to turn on/off, and press and hold for a short time to reset to the standby state.
- ② Press the SET button for a short time to enter the code recording state, and press and hold for 5 seconds to clear the code.
- ③ The MODE button switches the prompt mode, and there are three modes of beep/vibration/vibration +beep.

四. Fourth, the host keyboard

The keyboard is composed of the numbers 0-9 into 999 different encodings. The keyboard presses the numbers 0-9 to select the number to be called 1-999, and then presses the call key to make a call. If the number is selected incorrectly, you can press clear to re-select the number. You can also press + and - on the keyboard to select the number you want to call to make a call.

5. Host code value allocation

To prevent code-value conflicts between two hosts, you can randomly determine a set of code values by encoding the host through the following operations. In the case of power failure, press and hold the two numbering keys (clear key, 1 key) at the same time to power up until the buzzer emits "Didi". You can release the button to indicate that you have entered the code value allocation mode. In this mode, press the clear button until the buzzer emits "Didi" to indicate that the allocation is successful, so that the two host calls can be prevented from conflicting. You restart the pager at any time, and the assigned code value is different (note: the factory default code value has been set).

6. Code operation

When the extension is powered on and turned on, briefly press the SET button on the back of the extension to enter the code recording state, then press the number key corresponding to the host and then press the call button to complete the code matching.